


SIIG, INC.
I/O EXPANDER 3P

Card Type	Parallel card
Chipset Controller	Siig, Inc.
I/O Options	Parallel ports (3)
Maximum DRAM	N/A



CONNECTIONS			
Purpose :	Location	Purpose :	Location
25-pin parallel port	PR1	26-pin parallel port interface	PR3
26-pin parallel port interface	PR2		

PARALLEL PORT 1 CONFIGURATION			
LPT	P1/A	P1/B	P1/C
LPT3 (3BCh-3BEh)	Closed	Open	Open
LPT1 (378h-37Fh)	Open	Closed	Open
LPT2 (278h-27Fh)	Open	Open	Closed
Disabled	Open	Open	Open

Continued next page...

SIIG, INC.
I/O EXPANDER 3P

... continued from previous page.

PARALLEL PORT 1 INTERRUPT SELECTION									
IRQ	PA1/A	PA1/B	PA1/C	PA1/D	PA1/E	PA1/F	PA1/G	PA1/H	PA1/I
7	Open	Open	Open	Closed	Open	Open	Open	Open	Open
2/9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
3	Closed	Open	Open	Open	Open	Open	Open	Open	Open
4	Open	Closed	Open	Open	Open	Open	Open	Open	Open
5	Open	Open	Closed	Open	Open	Open	Open	Open	Open
10	Open	Open	Open	Open	Open	Closed	Open	Open	Open
11	Open	Open	Open	Open	Open	Open	Closed	Open	Open
12	Open	Open	Open	Open	Open	Open	Open	Closed	Open
15	Open	Open	Open	Open	Open	Open	Open	Open	Closed
Disabled	Open	Open	Open	Open	Open	Open	Open	Open	Open

PARALLEL PORT 2 CONFIGURATION			
LPT	P2/A	P2/B	P2/C
LPT1 (378h-37Fh)	Open	Closed	Open
LPT2 (278h-27Fh)	Open	Open	Closed
LPT3 (3BCh-3BEh)	Closed	Open	Open
Disabled	Open	Open	Open

PARALLEL PORT 2 INTERRUPT SELECTION									
IRQ	PA2/A	PA2/B	PA2/C	PA2/D	PA2/E	PA2/F	PA2/G	PA2/H	PA2/I
5	Open	Open	Closed	Open	Open	Open	Open	Open	Open
2/9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
3	Closed	Open	Open	Open	Open	Open	Open	Open	Open
4	Open	Closed	Open	Open	Open	Open	Open	Open	Open
7	Open	Open	Open	Closed	Open	Open	Open	Open	Open
10	Open	Open	Open	Open	Open	Closed	Open	Open	Open
11	Open	Open	Open	Open	Open	Open	Closed	Open	Open
12	Open	Open	Open	Open	Open	Open	Open	Closed	Open
15	Open	Open	Open	Open	Open	Open	Open	Open	Closed
Disabled	Open	Open	Open	Open	Open	Open	Open	Open	Open

PARALLEL PORT 3 CONFIGURATION			
LPT	P3/A	P3/B	P3/C
LPT2 (278h-27Fh)	Open	Open	Closed
LPT1 (378h-37Fh)	Open	Closed	Open
LPT3 (3BCh-3BEh)	Closed	Open	Open
Disabled	Open	Open	Open

Continued next page...

SIIG, INC.
I/O EXPANDER 3P

... continued from previous page.

PARALLEL PORT 3 INTERRUPT SELECTION									
IRQ	PA3/A	PA3/B	PA3/C	PA3/D	PA3/E	PA3/F	PA3/G	PA3/H	PA3/I
10	Open	Open	Open	Open	Open	Closed	Open	Open	Open
2/9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
3	Closed	Open	Open	Open	Open	Open	Open	Open	Open
4	Open	Closed	Open	Open	Open	Open	Open	Open	Open
5	Open	Open	Closed	Open	Open	Open	Open	Open	Open
7	Open	Open	Open	Closed	Open	Open	Open	Open	Open
11	Open	Open	Open	Open	Open	Open	Closed	Open	Open
12	Open	Open	Open	Open	Open	Open	Open	Closed	Open
15	Open	Open	Open	Open	Open	Open	Open	Open	Closed
Disabled	Open	Open	Open	Open	Open	Open	Open	Open	Open

PARALLEL PORT 2 & 3 ACTIVATION	
Chip	Socket
Controller	U2
Controller	U3
Note: To activate parallel ports 2 & 3 upgrade chips must be installed.	