


DIAMOND FLOWER, INC.

MCT-MIO

Card Type	Multi-I/O card
Chip Set	8250
Maximum Onboard Memory	None
I/O Options	Game port, parallel port, serial ports (2), Clock/Calendar external battery connector
Data Bus	8-bit ISA
Floppy drives supported	None



CONNECTIONS			
Function	Label	Function	Label
Clock/Calendar external battery connector	J1	Serial port 1	J4
Serial port 2	J2	Parallel port	J5
Game port	J3		

USER CONFIGURABLE SETTINGS			
Function	Label	Position	
Serial port 2 DCD normal operation	JP1/A	Pins 1 & 2 closed	
Serial port 2 DCD forced true	JP1/A	Pins 2 & 3 closed	
Serial port 2 DSR normal operation	JP1/B	Pins 1 & 2 closed	
Serial port 2 DSR forced true	JP1/B	Pins 2 & 3 closed	
Serial port 2 CTS normal operation	JP1/C	Pins 1 & 2 closed	
Serial port 2 CTS forced true	JP1/C	Pins 2 & 3 closed	
Serial port 1 DCD normal operation	JP2/A	Pins 1 & 2 closed	
Serial port 1 DCD forced true	JP2/A	Pins 2 & 3 closed	
Serial port 1 DSR normal operation	JP2/B	Pins 1 & 2 closed	
Serial port 1 DSR forced true	JP2/B	Pins 2 & 3 closed	
Serial port 1 CTS normal operation	JP2/C	Pins 1 & 2 closed	
Serial port 1 CTS forced true	JP2/C	Pins 2 & 3 closed	
Serial port 1 enabled	SW2/4	On	
Serial port 1 disabled	SW2/4	Off	
Serial port 1 enabled	SW2/5	On	
Serial port 1 disabled	SW2/5	Off	
Parallel port enabled	SW2/6	On	
Parallel port disabled	SW2/6	Off	

Continued on next page. . .

DIAMOND FLOWER, INC.

MCT-M10

... continued from previous page

USER CONFIGURABLE SETTINGS (CON'T)			
Function		Label	Position
í	Game port enabled	SW2/7	On
	Game port disabled	SW2/7	Off
í	Clock/Calendar enabled	SW2/8	On
	Clock/Calendar disabled	SW2/8	Off

DTE SELECTION			
Setting		JP4	JP3
	TX	Pins 1 & 2 closed	Pins 1 & 2 closed
	RX	Pins 3 & 4 closed	Pins 3 & 4 closed
	RTS	Pins 5 & 6 closed	Pins 5 & 6 closed
	CTS	Pins 7 & 8 closed	Pins 7 & 8 closed
	DTR	Pins 9 & 10 closed	Pins 9 & 10 closed

DCE SELECTION			
Setting		JP4	JP3
	TX/RX	Pins 1 & 3, 2 & 4 closed	Pins 1 & 3, 2 & 4 closed
	RTS/CTS	Pins 5 & 7, 6 & 8 closed	Pins 5 & 7, 6 & 8 closed
	DTR	Pins 9 & 10 closed	Pins 9 & 10 closed

PARALLEL PORT ADDRESS SELECTION			
Setting		SW2/3	
í	LPTA	Off	
	LPTB	On	

SERIAL PORT 1 & 2 ADDRESS SELECTION				
Serial port 1		Serial port 2	SW2/1	SW2/2
í	COM1 (3F8h)	COM2 (2F8h)	On	On
	COM2 (2F8h)	COM2 (2F8h)	Off	On
	COM3 (3E8h)	COM4 (2E8h)	On	Off

CLOCK/CALANDER INTERRUPT SELECTION			
IRQ		SW1/7	SW1/8
í	IRQ2	Off	On
	IRQ5	On	Off

SERIAL PORT 1 INTERRUPT SELECTION			
IRQ		SW1/3	SW1/4
í	IRQ4	Off	On
	IRQ3	On	Off

SERIAL PORT 2 INTERRUPT SELECTION			
IRQ		SW1/1	SW1/2
í	IRQ3	On	Off
	IRQ4	Off	On

Continued on next page. . .

DIAMOND FLOWER, INC.
MCT-M10

. . . continued from previous page

PARALLEL PORT INTERRUPT SELECTION		
IRQ	SW1/5	SW1/6
i IRQ7	On	Off
IRQ5	Off	On