


DIAMOND FLOWER, INC.

MIO-200

Card Type	Multi-I/O
Chipset	Unidentified
I/O Options	Clock/calendar, floppy drive interfaces (2), game port, parallel port, serial ports (2)
Data Bus	8-bit ISA
Floppy Drives Supported	Four 360KB drives



CONNECTIONS			
Function	Label	Function	Label
Floppy interface 1	CN-1	Game port	J3
Floppy interface 2	CN-2	Serial port 1	J4
External battery connector	J1	Parallel port	J5
Serial port 2	J2		

USER CONFIGURABLE SETTINGS			
Setting	Label	Position	
Port 2 CTS normal	JP1/A	Pins 1 & 2 closed	
Port 2 CTS forced high	JP1/A	Pins 2 & 3 closed	
Port 2 DSR normal	JP1/B	Pins 1 & 2 closed	
Port 2 DSR forced high	JP1/B	Pins 2 & 3 closed	
Port 2 DCD normal	JP1/C	Pins 1 & 2 closed	
Port 2 DCD forced high	JP1/C	Pins 2 & 3 closed	
Port 1 CTS normal	JP2/A	Pins 1 & 2 closed	
Port 1 CTS forced high	JP2/A	Pins 2 & 3 closed	
Port 1 DSR normal	JP2/B	Pins 1 & 2 closed	
Port 1 DSR forced high	JP2/B	Pins 2 & 3 closed	
Port 1 DCD normal	JP2/C	Pins 1 & 2 closed	
Port 1 DCD forced high	JP2/C	Pins 2 & 3 closed	
Parallel port address is 378h	DSW2/3	Off	
Parallel port address is 278h	DSW2/3	On	
Serial port 1 enabled	DSW2/4	On	
Serial port 1 disabled	DSW2/4	Off	
Serial port 2 enabled	DSW2/5	On	
Serial port 2 disabled	DSW2/5	Off	

Continued on next page. . .

DIAMOND FLOWER, INC.

MIO-200

... continued from previous page

USER CONFIGURABLE SETTINGS (CON'T)		
Setting	Label	Position
í Parallel port enabled	DSW2/6	On
Parallel port disabled	DSW2/6	Off
í Game port enabled	DSW2/7	On
Game port disabled	DSW2/7	Off
í Clock/calendar enabled	DSW2/8	On
Clock/calendar disabled	DSW2/8	Off

CLOCK/CALENDAR INTERRUPT SELECTION		
Setting	DSW1/7	DSW1/8
í IRQ2	Off	On
IRQ5	On	Off

PARALLEL PORT INTERRUPT SELECTION		
Setting	DSW1/5	DSW1/6
IRQ5	Off	On
í IRQ7	On	Off

SERIAL PORT ADDRESS SELECTION			
Port 1	Port 2	DSW2/1	DSW2/2
í 3F8h	2F8h	On	On
2F8h	3E8h	Off	On
3E8h	2E8h	On	Off

SERIAL PORT 1 INTERRUPT SELECTION		
Setting	DSW1/3	DSW1/4
IRQ3	On	Off
í IRQ4	Off	On

SERIAL PORT 2 INTERRUPT SELECTION		
Setting	DSW1/1	DSW1/2
í IRQ3	On	Off
IRQ4	Off	On

SERIAL PORT 1 MODE SELECTION	
Setting	JP4
í DTE	Pins 1 & 2, 3 & 4, 5 & 6, 7 & 8, 9 & 10 closed
DCE	Pins 1 & 2, 3 & 5, 4 & 6, 7 & 9, 8 & 10 closed

SERIAL PORT 2 MODE SELECTION	
Setting	JP3
í DTE	Pins 1 & 2, 3 & 4, 5 & 6, 7 & 8, 9 & 10 closed
DCE	Pins 1 & 3, 2 & 4, 5 & 7, 6 & 8, 9 & 10 closed