


SIMA TECHNOLOGY CO., LTD.
V.34P

Card Type	Modem (synchronous/asynchronous)
Chip Set	Unidentified
I/O Options	None
Maximum Data Rate	33.6Kbps
Maximum Fax Rate	14.4Kbps
Data Bus	16-bit ISA
Fax Class	Class I & II
Data Modulation Protocol	Bell 103A/212A ITU-T V.21, V.22, V.22bis, V.23, V.32, V.32bis, V.34 Rockwell V.FC
Fax Modulation Protocol	ITU-T V.17, V.21CH2, V.27ter, V.29
Error Correction/Compression	MNP5, V.42, V.42bis



CONNECTIONS			
Function	Label	Function	Label
Line out	CN1	Line in	CN2

PLUG-N-PLAY SELECTION			
Setting	JP18		JP20
Enabled	Closed		Pins 2 & 3 closed
Disabled	Open		Pins 1 & 2 closed

SERIAL PORT ADDRESS SELECTION			
Setting	JP18		JP19
3F8h (COM1:)	Closed		Closed
2F8h (COM2:)	Closed		Open
3E8h (COM3:)	Open		Closed
2E8h (COM4:)	Open		Open

Continued on next page . . .

. . . continued from previous page

INTERRUPT SELECTION									
Setting	JP8	JP9	JP10	JP11	JP12	JP13	JP14	JP15	JP16
i IRQ3	Open	Open	Open	Open	Open	Open	Open	Open	Closed
IRQ4	Open	Open	Open	Open	Open	Open	Open	Closed	Open
IRQ5	Open	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ11	Open	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ12	Open	Closed	Open	Open	Open	Open	Open	Open	Open
IRQ15	Closed	Open	Open	Open	Open	Open	Open	Open	Open

SUPPORTED STANDARD COMMANDS
Basic AT Commands
+++, 'comma', A/
A, B, D, E, H, L, M, N, O, P, Q, T, V, W, X, Y, Z
&C, &D, &F, &G, &K, &M, &P, &Q, &R, &S, &T, &V, &W, &X, &Y, &Z
Extended AT Commands
\A, \B, \G, \K, \L, \N, \W
%C, %F, %L, %Q, %T
Special AT Commands
#CID, :E, *H, -K,)M, @M, +MS, -Q
S-Registers
S0, S1, S2, S3, S4, S5, S6, S7, S8, S9, S10, S12, S14, S16, S18, S21, S22, S23, S24, S25, S27
S29, S30, S31, S32, S33, S36, S38, S39, S40, S46, S48, S86, S91, S92, S95, S201
Note: See MHI documentation for complete information.

Proprietary AT Command Set

See SIMA TECHNOLOGY CO., LTD. V.34S for a full command summary.