


SIMA TECHNOLOGY CO., LTD.

V.34PV

Card Type	Modem (synchronous/asynchronous)
Chip Set	Unidentified
I/O Options	Voice, microphone in, speaker out
Maximum Data Rate	33.6Kbps
Maximum Fax Rate	14.4Kbps
Data Bus	16-bit ISA
Fax Class	Class I & II
Data Modulation Protocol	Bell 103A/212A ITU-T V.21, V.22, V.22bis, V.23, V.32, V.32bis, V.34 Rockwell V.FC
Fax Modulation Protocol	ITU-T V.17, V.21CH2, V.27ter, V.29
Error Correction/Compression	MNP5, V.42, V.42bis



CONNECTIONS			
Function	Label	Function	Label
Line out	CN1	Microphone in	CN3
Line in	CN2	Speaker out	CN4

PLUG-N-PLAY SELECTION		
Setting	JP18	JP20
Enabled	Closed	Pins 2 & 3 closed
Disabled	Open	Pins 1 & 2 closed

SERIAL PORT ADDRESS SELECTION		
Setting	JP18	JP19
3F8h (COM1:)	Closed	Closed
2F8h (COM2:)	Closed	Open
3E8h (COM3:)	Open	Closed
2E8h (COM4:)	Open	Open

Continued on next page . . .

. . . continued from previous page

INTERRUPT SELECTION									
Setting	JP8	JP9	JP10	JP11	JP12	JP13	JP14	JP15	JP16
i IRQ3	Open	Open	Open	Open	Open	Open	Open	Open	Closed
IRQ4	Open	Open	Open	Open	Open	Open	Open	Closed	Open
IRQ5	Open	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ11	Open	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ12	Open	Closed	Open	Open	Open	Open	Open	Open	Open
IRQ15	Closed	Open	Open	Open	Open	Open	Open	Open	Open

SUPPORTED STANDARD COMMANDS	
Basic AT Commands	
+++, 'comma', A/	
A, B, D, E, H, L, M, N, O, P, Q, T, V, W, X, Y, Z	
&C, &D, &F, &G, &K, &M, &P, &Q, &R, &S, &T, &V, &W, &X, &Y, &Z	
Extended AT Commands	
\A, \B, \G, \K, \L, \N, \W	
%C, %F, %L, %Q, %T	
Special AT Commands	
#CID, :E, *H, -K,)M, @M, +MS, -Q	
S-Registers	
S0, S1, S2, S3, S4, S5, S6, S7, S8, S9, S10, S12, S14, S16, S18, S21, S22, S23, S24, S25, S27, S29	
S30, S31, S32, S33, S36, S38, S39, S40, S46, S48, S86, S91, S92, S95, S201	
Note: See MHI documentation for complete information.	

Proprietary AT Command Set

See SIMA TECHNOLOGY CO., LTD. V.34SV for a full command summary.