


ADAPTEC, INC. AHA-1540A, AHA-1542A

Data bus: 16-bit, ISA
 Size: Full-length, full-height card
 Hard drives supported: Up to seven SCSI devices
 Floppy drives supported: Two 360KB, 720KB, 1.2MB or 1.44MB



CONNECTIONS	
Function	Location
50-pin SCSI connector-external	CN1
50-pin SCSI connector-internal	CN2
34-pin data cable connector-floppy drive	CN4
4-pin connector-drive active LED	J5

SCSI ADDRESS			
SCSI ID	J1/jumper 4	J1/jumper 5	J1/jumper 6
7	open	open	open
6	closed	open	open
5	open	closed	open
4	closed	closed	open
3	open	open	closed
2	closed	open	closed
1	open	closed	closed
0	closed	closed	closed

Continued on next page . . .

ADAPTEC

AHA-1540A, AHA-1542A

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Location	Setting
í Synchronous negotiation disabled	J1/jumper 1	open
Synchronous negotiation enabled	J1/jumper 1	closed
í Factory test disabled	J1/jumper 2	open
Factory test enabled	J1/jumper 2	closed
í SCSI parity checking enabled	J1/jumper 3	open
SCSI parity checking disabled	J1/jumper 3	closed
í LA enable (Only on early W1542A)	J8	closed
LA disable (Only on early W1542A)	J8	open
í Auto request sense enabled	J9/jumper 1	open
Auto request sense disabled	J9/jumper 1	closed
í Factory configured - do not alter	J9/jumpers 2-4	open
í BOIS enabled	J11	closed
BIOS disabled	J11	open
í Floppy address 3F0-3F7h	J12	open
Floppy address 370-377h	J12	closed
í Floppy drive enabled	J13	closed
Floppy drive disabled	J13	open
í Floppy drive Interrupt is IRQ6	J17	pins 1 & 2 closed
Floppy drive Interrupt is IRQ10	J17	pins 2 & 3 closed
í Floppy drive DMA Request is DREQ2	J18	pins 1 & 2 closed
Floppy drive DMA Request is DREQ3	J18	pins 2 & 3 closed
í Floppy drive DMA Acknowledge is DACK2	J19	pins 1 & 2 closed
Floppy drive DMA Acknowledge is DACK3	J19	pins 2 & 3 closed

DMA CHANNEL				
DRQ	J1/Jumper 7	J1/Jumper 8	J14	J15
0	closed	closed	Jumper 1-closed	Jumper 1-closed
í 5	open	closed	Jumper 2-closed	Jumper 2-closed
6	closed	open	Jumper 3-closed	Jumper 3-closed
7	open	open	Jumper 4-closed	Jumper 4-closed

Continued on next page ...

ADAPTEC

AHA-1540A, AHA-1542A

... continued from previous page

INTERRUPT REQUEST				
IRQ	J1/Jumper 9	J1/Jumper 10	J1/Jumper 11	J16
9	open	open	open	Jumper 1-closed
10	closed	open	open	Jumper 2-closed
11	open	closed	open	Jumper 3-closed
12	closed	closed	open	Jumper 4-closed
14	open	open	closed	Jumper 5-closed
15	closed	open	closed	Jumper 6-closed

DMA TRANSFER RATE		
Speed	J1/jumper 12	J1/jumper 13
5.0	open	open
5.7	closed	open
6.7	open	closed
8.0	closed	closed

I/O PORT ADDRESS			
Address	J6/Jumper 1	J6/Jumper 2	J6/Jumper 3
334h	open	open	open
330h	open	open	closed
234h	open	closed	open
230h	open	closed	closed
134h	closed	open	open
130h	closed	open	closed

BUS WAIT STATE				
Delay	J7/jumper 1	J7/jumper 2	J7/jumper 3	J7/jumper 4
Disable	closed	open	open	open
100nsec	open	closed	open	open
200nsec	open	open	closed	open
300nsec	open	open	open	closed

BIOS ADDRESS		
Address	J10/jumper 1	J10/jumper 2
DC000h	open	open
CC000h	closed	open
D8000h	open	closed
C8000h	closed	closed

