


KOUWELL ELECTRONICS CORPORATION

KW-559AG

Q4/95

Data bus: 32-bit VL-bus
 Size: Three-quarter length, half-height card
 Hard drive supported: Two IDE(AT) drives
 Floppy drives supported: Two 360KB, 720KB, 1.2MB, or 1.44MB drives



CONNECTIONS	
Function	Location
9-pin serial port 1 - external, 10-pin serial port 1 internal	J1
10-pin serial port 2 - internal	J2
16-pin game port	J3
34-pin cable connector - floppy drive	J4
40-pin primary IDE(AT) connector	J5
25-pin parallel port - external	J7
4-pin connector - drive active LED	JP7

USER CONFIGURABLE SETTINGS		
Function	Location	Setting
Parallel port is bi-directional	JP3	open
Parallel port is unidirectional	JP3	closed
Floppy drive interface enabled	JP4/7	pins 1 & 2 closed
Floppy drive interface disabled	JP4/7	pins 2 & 3 closed
Parallel port IRQ 7 select	JP4/8	pins 2 & 3 closed
Parallel port IRQ 5 select	JP4/8	pins 1 & 2 closed
CPU speed is <=33MHz	JP6	open
CPU speed is >33MHz	JP6	closed

Continued on next page. . .

KOUWELL ELECTRONICS CORPORATION

KW-559AG

...continued from previous page

DRIVE SPEED CONFIGURATION		
Speed	JP5/1	JP5/2
0	pins 1 & 2 closed	pins 1 & 2 closed
1	pins 2 & 3 closed	pins 1 & 2 closed
2	pins 2 & 3 closed	pins 2 & 3 closed

SERIAL PORT 1 INTERRUPT SELECTION					
IRQ	JP1/1 pins 1 & 2	JP1/2 pins 1 & 2	JP1/3 pins 1 & 2	JP1/4 pins 1 & 2	JP1/5 pins 1 & 2
IRQ4	open	closed	open	open	open
IRQ3	closed	open	open	open	open
IRQ5	open	open	closed	open	open
IRQ9	open	open	open	closed	open
IRQ12	open	open	open	open	closed

SERIAL PORT 2 INTERRUPT SELECTION					
IRQ	JP1/1 pins 2 & 3	JP1/2 pins 2 & 3	JP1/3 pins 2 & 3	JP1/4 pins 2 & 3	JP1/5 pins 2 & 3
IRQ3	closed	open	open	open	open
IRQ4	open	closed	open	open	open
IRQ5	open	open	closed	open	open
IRQ9	open	open	open	closed	open
IRQ12	open	open	open	open	closed

PARALLEL PORT ADDRESS SELECTION		
LPT	JP4/5	JP4/6
378h	pins 1 & 2 closed	pins 2 & 3 closed
278h	pins 2 & 3 closed	pins 1 & 2 closed
3BCh	pins 1 & 2 closed	pins 1 & 2 closed
Disabled	pins 2 & 3 closed	pins 2 & 3 closed

SERIAL PORT 1 ADDRESS SELECTION		
COM	JP4/1	JP4/2
COM1 (3F8h)	pins 1 & 2 closed	pins 2 & 3 closed
COM3 (3E8h)	pins 2 & 3 closed	pins 1 & 2 closed
COM4 (2E8h)	pins 1 & 2 closed	pins 1 & 2 closed
Disabled	pins 2 & 3 closed	pins 2 & 3 closed

Continued on next page. . .

KOUWELL ELECTRONICS CORPORATION

KW-559AG

SERIAL PORT 2 ADDRESS SELECTION		
COM	JP4/3	JP4/4
COM2 (2F8h)	pins 1 & 2 closed	pins 2 & 3 closed
COM3 (3E8h)	pins 1 & 2 closed	pins 1 & 2 closed
COM4 (2E8h)	pins 2 & 3 closed	pins 1 & 2 closed
Disabled	pins 2 & 3 closed	pins 2 & 3 closed

GAME PORT CONFIGURATION		
Mode	JP2/1	JP2/2
Enabled	closed	closed
Disabled	open	open