


DATA TECHNOLOGY CORPORATION

DTC2278E (400518-89A)

Data Bus
 Card Size
 Hard Drives supported
 Floppy drives supported

32-bit VESA Local Bus
 Three-quarter length, half-height card
 Four IDE (AT) or EIDE drives
 Two 360KB, 720KB, 1.2MB, or 1.44MB drives



| CONNECTIONS | | | |
|---------------------------------------|----------|------------------------------------|----------|
| Function | Location | Function | Location |
| 10-pin serial port 2 - internal | J2 | 40-pin secondary IDE(AT) connector | J6 |
| 9-pin serial port 1 - external | J3 | 40-pin primary IDE(AT) connector | J7 |
| 16-pin game port | J4 | 4-pin connector - drive active LED | J8 |
| 34-pin cable connector - floppy drive | J5 | 25-pin parallel port - external | J9 |

| USER CONFIGURABLE SETTINGS | | | |
|----------------------------|-------|----------|--|
| Function | Label | Position | |
| Game port enabled | W14 | Closed | |
| Game port disabled | W14 | Open | |

| SERIAL PORT 1 ADDRESS SELECTION | | | |
|---------------------------------|-------------------|-------------------|--|
| COM | W5 | W6 | |
| iCOM1 (3F8h) | Pins 1 & 2 closed | Pins 2 & 3 closed | |
| COM3 (3E8h) | Pins 2 & 3 closed | Pins 1 & 2 closed | |
| Disabled | Pins 1 & 2 closed | Pins 1 & 2 closed | |

Notes: COM1 & COM3 are automatically configured to IRQ4. COM2 & COM4 are automatically configured to IRQ3.

| SERIAL PORT 2 ADDRESS SELECTION | | | |
|---------------------------------|-------------------|-------------------|--|
| COM | W3 | W4 | |
| iCOM2 (2F8h) | Pins 1 & 2 closed | Pins 2 & 3 closed | |
| COM4 (2E8h) | Pins 2 & 3 closed | Pins 1 & 2 closed | |
| Disabled | Pins 1 & 2 closed | Pins 1 & 2 closed | |

Notes: COM1 & COM3 are automatically configured to IRQ4. COM2 & COM4 are automatically configured to IRQ3.

Continued on next page ...

DATA TECHNOLOGY CORPORATION

DTC 2278E (VERSION 2)

.... continued from previous page

| PARALLEL PORT ADDRESS SELECTION | | |
|---------------------------------|-------------------|-------------------|
| LPT | W1 | W2 |
| i LPT1 (378h) | Pins 2 & 3 closed | Pins 1 & 2 closed |
| LPT2 (278h) | Pins 1 & 2 closed | Pins 2 & 3 closed |
| LPT3 (3BCh) | Pins 2 & 3 closed | Pins 2 & 3 closed |
| Disabled | Pins 1 & 2 closed | Pins 1 & 2 closed |

| PARALLEL PORT MODE CONFIGURATION | | |
|----------------------------------|-------------------|-------------------|
| Mode | W7 | W22 |
| ECP | Pins 2 & 3 closed | Pins 1 & 2 closed |
| EPP | Pins 1 & 2 closed | Pins 2 & 3 closed |
| i Printer | Pins 2 & 3 closed | Pins 2 & 3 closed |

Note: You must select a DMA channel when using ECP mode.

| DMA CONFIGURATION | | | | |
|-------------------|--------|--------|--------|--------|
| Mode | W8 | W9 | W10 | W11 |
| 1 | Closed | Open | Closed | Open |
| i 3 | Open | Closed | Open | Closed |

| SERIAL PORT 1 INTERRUPT SELECTION | | | |
|-----------------------------------|--------|--------|--------|
| IRQ | W19 | W20 | W21 |
| IRQ3 | Open | Closed | Open |
| i IRQ4 | Open | Open | Closed |
| IRQ5 | Closed | Open | Open |

| SERIAL PORT 2 INTERRUPT SELECTION | | | |
|-----------------------------------|--------|--------|--------|
| IRQ | W16 | W17 | W18 |
| i IRQ3 | Open | Open | Closed |
| IRQ4 | Open | Closed | Open |
| IRQ5 | Closed | Open | Open |

| PARALLEL PORT INTERRUPT | | |
|-------------------------|--------|--------|
| IRQ | W12 | W13 |
| i IRQ7 | Open | Closed |
| IRQ5 | Closed | Open |

| MISCELLANEOUS TECHNICAL NOTES |
|---|
| The floppy controller is automatically configured. When a cable is attached, it is enabled; when no cable is attached it is disabled. |