TOP MICROSYSTEMS, INC.


TE 2003

NIC Type Ethernet
Transfer Rate 10Mbps
Data Bus 16-bit ISA
Topology Linear bus

Wiring Type Unshielded twisted pair RG58A/U 50ohm coaxial

AUI transceiver via DB-15

Boot ROM Available



BOOT ROM		
Setting JP1/A		
í Disabled	Open	
Enabled	Closed	

BOOT ROM ADDRESS SELECT				
Address	JP1/B	JP1/C	JP1/D	
í C800h	Open	Closed	Open	
C000h	Open	Open	Open	
C400h	Open	Open	Closed	
CC00h	Open	Closed	Closed	
D000h	Closed	Open	Open	
D400h	Closed	Open	Closed	
D800h	Closed	Closed	Open	
DC00h	Closed	Closed	Closed	

Continued on next page . . .

TOP MICROSYSTEMS, INC. T E 2003

. . . continued from previous page

	CABLE TYPE			
Туре	JP2/A	JP2/B	JP2/C	JP2/D
í Thin Ethernet	Not installed	Not installed	Installed	Installed
Thick Ethernet	Not installed	Installed	Installed	Not installed
Unshielded twisted pair	Installed	Installed	Not installed	Not installed

INTERRUPT SELECT								
í IRQ	JP5/A	JP5/B	JP5/C	JP5/D	JP5/E	JP5/F	JP5/G	JP5/H
IRQ3	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ2	Closed	Open						
IRQ4	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ5	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ11	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ12	Open	Open	Open	Open	Open	Open	Closed	Open
IRQ15	Open	Closed						

	I/O ADDRESS SELECT	
Address	JP1/E	JP1/F
í 300h	Open	Open
320h	Open	Closed
340h	Closed	Open
360h	Closed	Closed

SYSTEM TYPE				
Туре	JP3			
í AT compatible	Pins 1 & 2 closed			
Non-AT compatible	Pins 2 & 3 closed			

DIAGNOSTIC LED		
Status	Condition	
On	Network connection is good	
Off	Network connection is broken	