


MOTOROLA, INC.

6520/6560 MPROUTER HUB CARD

NIC Type	Ethernet Hub
I/O Options	Daisy-chain connector
Network Transfer Rate	10Mbps
Data Bus	8-bit ISA
Topology	Star
Wiring Type	Unshielded twisted pair
Boot ROM	Not available



CONNECTIONS			
Function	Label	Function	Label
Unshielded twisted pair port 1	CN1	Unshielded twisted pair port 5	CN5
Unshielded twisted pair port 2	CN2	Unshielded twisted pair port 6	CN6
Unshielded twisted pair port 3	CN3	Daisy-chain connector	CN7
Unshielded twisted pair port 4	CN4		

Note: Up to four hub cards may be connected via the daisy-chain connector.

USER CONFIGURABLE SETTINGS		
Setting	Label	Position
í Factory configured - do not alter	JP1/D	Closed
í Factory configured - do not alter	JP2	Open

BASE I/O ADDRESS				
Setting	Slot Installed	JP1/A	JP1/B	JP1/C
300h	8	Closed	Closed	Closed
310h	7	Open	Closed	Closed
320h	6	Closed	Open	Closed
330h	5	Open	Open	Closed
340h	4	Closed	Closed	Open
350h	3	Open	Closed	Open
360h	2	Closed	Open	Open
370h	1	Open	Open	Open

Continued on next page. . .

MOTOROLA, INC.
6520/6560 MPROUTER HUB CARD

. . . continued from previous page

DIAGNOSTIC LED(S)			
LED	Color	Status	Condition
LED1	Unidentified	On	Network connection on Port 1 is good, or self-test in progress
LED1	Unidentified	Off	Network connection on Port 1 is broken
LED2	Unidentified	On	Network connection on Port 2 is good, or self-test in progress
LED2	Unidentified	Off	Network connection on Port 2 is broken
LED3	Unidentified	On	Network connection on Port 3 is good, or self-test in progress
LED3	Unidentified	Off	Network connection on Port 3 is broken
LED4	Unidentified	On	Network connection on Port 4 is good, or self-test in progress
LED4	Unidentified	Off	Network connection on Port 4 is broken
LED5	Unidentified	On	Network connection on Port 5 is good, or self-test in progress
LED5	Unidentified	Off	Network connection on Port 5 is broken
LED6	Unidentified	On	Network connection on Port 6 is good, or self-test in progress
LED6	Unidentified	Off	Network connection on Port 6 is broken

MISCELLANEOUS TECHNICAL NOTE

This card is designed for use in Motorola's 6520/6560 MPRouter system and will not function in another system. See documents M3596 and M3597 for more information.