
AT&T STARLAN

NIC Type Ethernet
Network Transfer Rate 1Mbps
Data Bus 8-bit ISA
Topology Linear Bus/Star

Wire Type Unshielded twisted pair (1Base-5)

Boot ROM Not available



| CONNECTIONS | | | | | |
|---|-------|--|-------|--|--|
| Function | Label | Function | Label | | |
| Unshielded twisted pair for telephone wiring | CN1 | Standard unshielded twisted pair receive connector | CN3 | | |
| Standard unshielded twisted pair transmit connector | CN2 | | | | |

| USER CONFIGURABLE SETTINGS | | | | | |
|-------------------------------------|-------|--------------------------|--|--|--|
| Setting | Label | Position | | | |
| Base I/O address is 360h | JP1 | Pins 1 & 2, 3 & 4 closed | | | |
| Base I/O address is 368h | JP1 | Pins 2 & 3, 4 & 5 closed | | | |
| í Factory configured - do not alter | JP3 | Pins 2 & 3, 4 & 5 closed | | | |

| INTERRUPT | | | | | |
|-----------|-------------------|-------------------|--|--|--|
| Setting | JP4 | JP5 | | | |
| IRQ2 | Open | Pins 2 & 3 closed | | | |
| IRQ3 | Open | Pins 1 & 2 closed | | | |
| IRQ4 | Pins 2 & 3 closed | Open | | | |
| IRQ7 | Pins 1 & 2 closed | Open | | | |

Continued on next page. . .

AT&T STARLAN

. . . continued from previous page

| SHARED RAM ADDRESS | | | | | | | | |
|--------------------|--------|--------|--------|--------|--------|--------|--------|--------|
| Setting | JP2/A | JP2/B | JP2/C | JP2/D | JP2/E | JP2/F | JP2/G | JP2/H |
| 80000h | Closed | Open |
| 90000h | Open | Closed | Open | Open | Open | Open | Open | Open |
| A0000h | Open | Open | Closed | Open | Open | Open | Open | Open |
| B0000h | Open | Open | Open | Closed | Open | Open | Open | Open |
| C0000h | Open | Open | Open | Open | Closed | Open | Open | Open |
| D0000h | Open | Open | Open | Open | Open | Closed | Open | Open |
| E0000h | Open | Open | Open | Open | Open | Open | Closed | Open |
| F0000h | Open | Closed |