


QUATECH, INC. QS-1000

Category	I/O Controller
Chipset Controller	16550 UART
I/O Options Supported	Serial ports (4)
Maximum Onboard Memory	N/A



CONNECTIONS			
Purpose :	Location	Purpose :	Location
Serial port 1 - RJ-11	CN1	Serial port 3 - RJ-11	CN3
Serial port 2 - RJ-11	CN2	Serial port 4 - RJ-11	CN4

INPUT CLOCK FREQUENCY	
Frequency	J1
1.8432MHz	Pins 1 & 2, 4 & 5, 3 & 6 closed
18.432MHz	Pins 2 & 5 closed
9.216MHz	Pins 2 & 3, 4 & 5 closed
3.6864MHz	Pins 1 & 2, 5 & 6 closed

PORT 1 HANDSHAKE OPTIONS	
Setting	J2
RTS/CTS handshake, DTR/DSR loopback	Pins 1 & 2, 4 & 5, 3 & 6 closed
RTS/CTS loopback, DTR/DSR handshake	Pins 1 & 4, 2 & 3, 5 & 6 closed
RTS/CTS loopback, DTR/DSR loopback	Pins 1 & 4, 3 & 6 closed

PORT 2 HANDSHAKE OPTIONS	
Setting	J3
RTS/CTS handshake, DTR/DSR loopback	Pins 1 & 2, 4 & 5, 3 & 6 closed
RTS/CTS loopback, DTR/DSR handshake	Pins 1 & 4, 2 & 3, 5 & 6 closed
RTS/CTS loopback, DTR/DSR loopback	Pins 1 & 4, 3 & 6 closed

Continued on next page . . .

QUATECH, INC.
QS-1000

. . . continued from previous page

PORT 3 HANDSHAKE OPTIONS	
Setting	J4
RTS/CTS handshake, DTR/DSR loopback	Pins 1 & 2, 4 & 5, 3 & 6 closed
RTS/CTS loopback, DTR/DSR handshake	Pins 1 & 4, 2 & 3, 5 & 6 closed
RTS/CTS loopback, DTR/DSR loopback	Pins 1 & 4, 3 & 6 closed

PORT 4 HANDSHAKE OPTIONS	
Setting	J5
RTS/CTS handshake, DTR/DSR loopback	Pins 1 & 2, 4 & 5, 3 & 6 closed
RTS/CTS loopback, DTR/DSR handshake	Pins 1 & 4, 2 & 3, 5 & 6 closed
RTS/CTS loopback, DTR/DSR loopback	Pins 1 & 4, 3 & 6 closed