


# CREATIVE LABS, INC. SOUNDBLASTER AWE32 IDE (CT3990 & CT3999)

**Card Type** Sound card  
**Chip Set** Creative Technology  
**Maximum Onboard Memory** Unidentified  
**I/O Options** CD-ROM interface, microphone connector, line in connector, line out connector, speaker out connector, game/MIDI port, PC internal speaker, CD-ROM audio in connectors (2), feature connector  
**Data Bus** 16-bit ISA



CONNECTIONS			
Function	Label	Function	Label
Line in connector	CN1	CD-ROM audio in connector	CN6
Microphone connector	CN2	CD-ROM audio in connector	CN7
Line out connector	CN3	Feature connector	CN8
Speaker out connector	CN4	CD-ROM interface	CN10
Game/MIDI port	CN5	PC internal speaker	JP7

USER CONFIGURABLE SETTINGS			
Function	Label	Position	
í Factory configured – do not alter	APSD	Unidentified	
í Factory configured – do not alter	CN9	Unidentified	
í Factory configured – do not alter	IFSD	Unidentified	
í MP-401 I/O enabled	MFBE N	Closed	
MP-401 I/O disabled	MFBE N	Open	
í Factory configured – do not alter	SPDIF	Unidentified	

Continued on next page. . .

CREATIVE LABS, INC.  
SOUNDBLASTER AWE32 IDE (CT3990 & CT3999)

. . . continued from previous page

**DRAM CONFIGURATION**

Note: Board is factory installed with 512KB memory. The maximum amount of onboard memory is unidentified.

**DRAM JUMPER CONFIGURATION**

<b>Setting</b>	<b>JP2</b>
Memory upgrade disabled	Pins 2 & 3 closed
Memory upgrade enabled	Pins 1 & 2 closed