


CREATIVE LABS, INC. SOUNDBLASTER AWE32 IDE/MKP CSP (CT3900)

Card Type Sound card
Chip Set Creative Technology
Maximum Onboard Memory Unidentified
I/O Options CD-ROM interfaces (2), microphone connector, line in connector, line out connector, speaker out connector, game/MIDI port, PC internal speaker, CD-ROM audio in connectors (2), feature connector
Data Bus 16-bit ISA



CONNECTIONS			
Function	Label	Function	Label
Line in connector	CN1	CD-ROM audio in connector	CN7
Microphone connector	CN2	Feature connector	CN8
Line out connector	CN3	Panasonic CD-ROM interface	CN9
Speaker out connector	CN4	CD-ROM interface	CN10
Game/MIDI port	CN5	PC internal speaker	JP19
CD-ROM audio in connector	CN6		

USER CONFIGURABLE SETTINGS			
Function	Label	Position	
í Factory configured – do not alter	JP1	Unidentified	
í Joystick enabled	JP14	Closed	
Joystick disabled	JP14	Open	
í MP-401 enabled	JP15	Closed	
MP-401 disabled	JP15	Open	
í MP-401 I/O address select 330	JP16	Closed	
MP-401 I/O address select 300	JP16	Open	
í Factory configured – do not alter	JP20	Unidentified	
í Factory configured – do not alter	JP21	Unidentified	
í Factory configured – do not alter	SPDIF	Unidentified	

Continued on next page. . .

CREATIVE LABS, INC.
SOUNDBLASTER AWE32 IDE/MKP CSP (CT3900)

... continued from previous page

DRAM CONFIGURATION

Note: Board is factory installed with 512KB memory. The maximum amount of onboard memory is unidentified.

DRAM JUMPER CONFIGURATION

Setting	JP2
Memory upgrade disabled	Pins 2 & 3 closed
Memory upgrade enabled	Pins 1 & 2 closed

AUDIO I/O ADDRESS SELECTION

Address	JP17	JP18
220	Closed	Closed
240	Open	Closed
260	Closed	Open
280	Open	Open

CSP CHIP SELECTION

Setting	APSD	IFSD
Enabled	Open	Open
Disabled	Closed	Closed

IDE PORT SELECTION

Port	JP2	JP3
Secondary	Open	Closed
Tertiary	Closed	Open
Quaternary	Open	Open
Disabled	Closed	Closed

IDE INTERRUPT SELECTION

IRQ	JP5	JP6	JP7	JP8	JP9
10	Closed	Open	Open	Open	Open
11	Open	Closed	Open	Open	Open
12	Open	Open	Closed	Open	Open
14	Open	Open	Open	Closed	Open
15	Open	Open	Open	Open	Closed