


LOGICODE TECHNOLOGY, INC.

96HV

Card Type	Modem (synchronous/asynchronous)
Chipset	Unidentified
Maximum Data Rate	9600bps
Data Modulation	Unidentified (V.32 maximum)
Error	MNP5, V.42, V.42bis
Correction/Compression	
Data Bus	8-bit ISA
Card Size	Unidentified



CONNECTIONS			
Function	Label	Function	Label
Telephone line	CN1	Telephone line	CN2

SERIAL PORT CONFIGURATION							
Address	IRQ	SW1/1	SW1/2	SW1/3	SW1/4	SW1/5	SW1/6
COM1:	4	Off	On	Off	Off	On	On
COM2:	3	On	Off	Off	Off	On	Off
COM3:	4	Off	On	Off	Off	Off	On
COM4:	3	On	Off	Off	Off	Off	Off

SUPPORTED STANDARD COMMANDS	
Basic AT Commands	
+++ , 'comma' , A/	
A, B, E, F, H, L, M, N, O, P, Q, T, V, W, X, Y, Z	
&C, &D, &F, &G, &J, &K, &L, &P, &R, &S, &T, &V, &W, &X, &Y, &Z	
Extended AT Commands	
\A, \B, \G, \K, \L, \N, \O, \T, \U, \Y, \Z	
%C, %E, %L, %Q	
S-Registers	
S0, S1, S2, S3, S4, S5, S6, S7, S8, S9, S10, S11, S12, S18, S25, S26, S30, S36, S38, S46	
S48, S82, S86, S91, S95	
Note: See MHI help file for complete information.	

Continued on next page. . .

LOGICODE TECHNOLOGY, INC.
96HV

. . . continued from previous page

UNIDENTIFIED COMMANDS	
Command	Default
S14	0
S16	0
S21	0
S22	118
S23	7
S27	64
S40	57
S41	1

Proprietary AT Command Set

See LOGICODE TECHNOLOGY, INC. 14.4HV for a full command summary.