


# UNIDENTIFIED IDE PLUS-V3

Data Bus  
Card Size  
Hard Drives supported  
Floppy drives supported

16-bit ISA  
Half-length, full-height card  
Two IDE (AT) drives  
Two 360KB, 720KB, 1.2MB, or 1.44MB drives



CONNECTIONS			
Function	Location	Function	Location
40-pin IDE (AT) Interface connector-internal	CN1	9-pin serial port 1 - external	CN5
34-pin control cable connector - floppy drive	CN2	15-pin game port - external	CN6
2-pin connector - drive active LED	CN3	25-pin parallel port - external	CN7
10-pin serial port 2 - internal	CN4		

USER CONFIGURABLE SETTINGS			
Function	Label	Position	
Parallel port address is 378-37Fh (LPT1)	JP1	Pins 1 & 2 closed	
Parallel port address is 278-27Fh (LPT2)	JP1	Pins 2 & 3 closed	
Serial port 1 enabled	JP2	Pins 1 & 2 closed	
Serial port 1 disabled	JP2	Pins 2 & 3 closed	
Floppy drive controller enabled	JP3	Pins 1 & 2 closed	
Floppy drive controller disabled	JP3	Pins 2 & 3 closed	
IDE(AT) interface enabled	JP4	Pins 1 & 2 closed	
IDE(AT) interface disabled	JP4	Pins 2 & 3 closed	
Serial port 2 address is 2F8-2FFh	JP5	Pins 1 & 2 closed	
Serial port 2 address is 2E8-2EFh	JP5	Pins 2 & 3 closed	
Serial port 1 address is 3F8-3FFh	JP6	Pins 1 & 2 closed	
Serial port 1 address is 3E8-3EFh	JP6	Pins 2 & 3 closed	
Serial port 2 enabled	JP7	Pins 1 & 2 closed	
Serial port 2 disabled	JP7	Pins 2 & 3 closed	
Parallel port enabled	JP8	Pins 1 & 2 closed	
Parallel port disabled	JP8	Pins 2 & 3 closed	
Game port enabled	JP9	Pins 2 & 3 closed	
Game port disabled	JP9	Pins 1 & 2 closed	

Continued on next page . . .

# UNIDENTIFIED IDE PLUS-V3

... continued from previous page

SERIAL PORT 1 INTERRUPT SELECTION					
IRQ	JP12/ pins 1 & 2	JP12/ pins 3 & 4	JP12/ pins 5 & 6	JP12/ pins 7 & 8	JP12/ pins 9 & 10
IRQ3	Closed	Open	Open	Open	Open
IRQ4	Open	Closed	Open	Open	Open
IRQ5	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Closed	Open
IRQ9	Open	Open	Open	Open	Closed

SERIAL PORT 2 INTERRUPT SELECTION					
IRQ	JP13/ pins 1 & 2	JP13/ pins 3 & 4	JP13/ pins 5 & 6	JP13/ pins 7 & 8	JP13/ pins 9 & 10
IRQ3	Closed	Open	Open	Open	Open
IRQ4	Open	Closed	Open	Open	Open
IRQ5	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Closed	Open
IRQ9	Open	Open	Open	Open	Closed

PARALLEL PORT INTERRUPT SELECTION					
IRQ	JP14/ pins 1 & 2	JP14/ pins 3 & 4	JP14/ pins 5 & 6	JP14/ pins 7 & 8	JP14/ pins 9 & 10
IRQ3	Closed	Open	Open	Open	Open
IRQ4	Open	Closed	Open	Open	Open
IRQ5	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Closed	Open
IRQ9	Open	Open	Open	Open	Closed