
## SIIG, INC. I/O EXTENSION-A.3

Card Type Multi-I/O card
Chip Set Unidentified
Maximum Onboard Memory None

I/O Options game port, parallel port (2), serial ports (2)
Data Bus 8-bit ISA

Floppy drives supported None



CONNECTIONS				
Purpos	.ocation	Purp∈se	Location	
25-pin parallel port	CN1	16-pin Game port	CN4	
9-pin serial port external	CN2	26-pin Parallel port internal	CN5	
10-pin serial port internal	CN3			

Continued on next page. . .

## SIIG, INC.

## I/O EXTENSION-A.3

. . .continued from previous page

PARALLEL PORT INTERRUPT SELECT				
IRC	JP2/A	JP2/B		
í IRQ7	Open	Closed		
IRQ5	Closed	Open		

COM SELECT				
Prima y port	Seco⊨ dary port	€ <b>N</b> 1/1	₹ N1/2	
Disable	Disable	Off	Off	
COM1	COM2	Off	On	
COM2	COM3	On	Off	
COM3	COM4	On	On	

ADDRESS SELECT		
Address	SW1/3	
378-37Ah	Off	
278-27Ah	On	

GAME PORT SELECT		
Setting	SW1/4	
í Enabled	Off	
Disabled	On	

SERIAL PORT 1 INTERRUPT SELECT				
IRQ	JP1/A	JP1/B	JP1/C	JP1/D
IRQ2	Closed	Open	Open	Open
IRQ3	Open	Closed	Open	Open
IRQ4	Open	Open	Closed	Open
IRQ5	Open	Open	Open	Closed

SERIAL PORT 2 INTERRUPT SELECT				
IRQ	JP3/A	JP3/B	JP3/C	JP3/D
IRQ2	Closed	Open	Open	Open
IRQ3	Open	Closed	Open	Open
IRQ4	Open	Open	Closed	Open
IRQ5	Open	Open	Open	Closed

FACTORY CONFIGURED SETTING		
Jumper Setting		
JP4/A	N/A	
JP4/B	N/A	